



## M1

### DIGITAL STEREO MIXER

-  Extended Compatibility
-  Audio Streaming
-  Effects
-  Microphone Input
-  USB Player
-  USB Powered

The M1 is an ultra compact and lightweight 4-channel digital stereo mixer with BT to use as a “traditional mixer” or USB Audio Interface. When used as a USB Audio Interface, it can be connected to a PC, allowing the production of online content with high-fidelity sound, either for real-time transmission (streaming) or production of offline videos and podcasts. You can also record directly to a USB stick.

#### Product Type

Digital Mixing Console (USB Audio Interface)

#### Mixer

4 Channels (2 x Mono | 1 x Stereo)

#### DSP Technology

24bit | 192kHz

#### Effects

Ambience, Bathroom, Room, Plate, Spring, Hall, Warehouse, Cathedral, Gated Reverb, Chorus, Chorus Reverb, Phaser, Phaser Reverb, Flanger, Flanger Reverb, Rotary, Delay

#### Wireless Connection System

BT v5.0

#### Wireless Range

10m (32.8ft)

#### Audio Signal Inputs

BT | Microphone (+48V) | Instrument (HI-Z) | USB | AUX | CD Player | PC (2 Channels)

#### Input Connectors

2 x XLR / TRS combo | 1 x 3.5mm Stereo Jack | 1 x USB | 1 x Stereo RCA | 1 x USB 2.0

#### Audio Signal Outputs

Main Output | Headphones | PC (2 Channels)

#### Output Connectors

2 x Balanced TRS | 1 x 3.5mm Stereo Jack | 1 x USB 2.0

#### Power Input

Power Supply: AC 100V - 240V 50Hz/60Hz | DC 5V - 2A

#### Power Consumption

10W (2A)

#### Special Features

HI-Z, Low Cut, EQ (LOW, MID, HIGH), Phantom Power (+48V), Effects, USB Stick Recording, PC Recording

#### Construction

Reinforced Plastic

#### Dimensions (WxHxD)

153 x 64 x 175mm (6 x 2.5 x 6.9 in)

#### Net Weight

0.6kg (1.3lb)

#### Shipping Weight

0.9kg (2lb)